

FOCUSAUDIO

Prestige SE Series



Prestige SE Series Specification

	FPC SE Center	FP50 SE	FP60 SE	FP70 SE	FP80 SE	FP88 SE	FP90 SE
Frequency Response:	45 Hz-25 kHz ± 3dB	45 Hz-25 kHz ± 3dB	40 Hz-25 kHz ± 3dB	35 Hz-25 kHz ± 3dB	40 Hz-25 kHz ± 3dB	30 Hz-25 kHz ± 3dB	25 Hz-25 kHz ± 3dB
Sensitivity:	90 dB/2.83V/1m	85 dB/2.83V/1m	86 dB/2.83V/1m	86 dB/2.83V/1m	90 dB/2.83V/1m	90 dB/2.83V/1m	87 dB/2.83V/1m
Impedance:	Nominal 4 Ohms	Nominal 8 Ohms	Nominal 8 Ohms	Nominal 8 Ohms	Nominal 4 Ohms	Nominal 4 Ohms	Nominal 8 Ohms
Recommended Power:	20 - 300 W	20 - 300 W	20 - 300 W	20 - 300 W	20 - 500 W	20 - 500 W	50 - 500 W
Drivers:	One 1" tweeter Two 5.5" woofers	One 1" tweeter One 5.5" woofer	One 1" tweeter One 7" woofer	One 1" tweeter One 7" woofer	One 1" tweeter Two 5.5" woofers	One 1" tweeter Two 7" woofers	One 1" tweeter One 5.5" midrange One 9" woofers
Size:	7.5" x 22.5" x 10"	13" x 7" x 10"	17" x 8" x 12"	38" x 8" x 10"	38" x 7.5" x 10"	43" x 8" x 13"	43" x 9.5" x 15.5"
Weight:	28 lbs each	19 lbs each	28 lbs each	55 lbs each	50 lbs each	70 lbs each	88 lbs each

Focus Audio Inc.

Address: 43 Riviera Drive, Unit #10, Markham, Ontario, Canada L3R 5J6
 Telephone: 905 415 8773 Fax: 905 415 0456
 www.focusaudio.com contact@focusaudio.com

Due to continuous research and development, Focus Audio reserve the right to amend or change any specification without notice.

FOCUSAUDIO

Prestige SE Series



Prestige SE Series

FPC SE Center / FP50 SE / FP60 SE / FP70 SE / FP80 SE / FP88 SE / FP90 SE